

# CYBER PAK



3-in-1 Audio Management System

DATA SHEET



## KEY FEATURES

4-Channel Dimmer/Relay/MIDI Pack

Individual DMX Address for each Channel

Selectable Modes (Dimmer or Switch Pack)

(16) Internal Chase Macros with Fade In/Out

DMX Fail (loss of signal) Settings: HOLD/OFF/ON

Power Failure Memory

The **Cyber Pak** offers three modes: Chaser Mode, Dimmer Mode, and MIDI Mode that will give you many options.

The Chaser mode includes 4-channel chase controller with 10 built-in chase programs so you can start right out of the box. The Dimmer mode comes with 1,2, or 4-channel dimmer pack with 4 individual DMX channels. The MIDI mode allows the device to receive MIDI notes 001 - 128. All of the chase programs can be set to fade-in or fade-out.

The digital displays show the current program and will make it easy to control the show. There are MIDI In and MIDI through connection available on the Cyber Pak. This Cyber Pak is perfect for that entertainer that needs complete control over all their lighting and entertainment equipment.



# CYBER PAK



3-in-1 Audio Management System

## SPECIFICATIONS

### FEATURES:

- 4-Channel Dimmer/Relay/MIDI Pack
- Individual DMX Address for each Channel
- Selectable Modes (Dimmer or Switch Pack)
- (16) Internal Chase Macros with Fade In/Out
- DMX Fail (loss of signal) Settings: HOLD/OFF/ON
- Power Failure Memory

### DIMMER MODE:

- (4) Channel Dimmer (1, 2 or 4 Channel Option)
- Individual Channel Assignment & Output Limiter

### RELAY MODE:

- 4-Channel Relay (1, 2 or 4 Channel Option)
- Individual Channel Assignment

### CHASER MODE:

- 4-Channel Chase Controller
- 16 Internal Chase Programs
- Adjustable Fade Times

### MIDI MODE:

- Receives MIDI Notes 001-128 Program
- MIDI In & MIDI Through Connections

### CONTROL / CONNECTIONS:

- Two 3-prong Edison Sockets per Channel (8 total)
- 5-pin MIDI IN/OUT Ports
- 5-pin XLR IN/OUT Ports
- 4-Button LED Display Control Panel
- Master Power Switch

### SIZE / WEIGHT:

- Length: 8.3" (212mm)
- Width: 10.4" (265mm)
- Vertical Height: 3.0" (75mm)
- Weight: 8.0 lbs. (3.6kg)

### ELECTRICAL / THERMAL:

- AC 120V 50/60Hz 20A Max
- 2,400W Max Power Consumption (600W per channel)
- NOTE: Main Power Cord is Bare Wire, 3-Prong Connector Not Included.

### APPROVALS / RATINGS:

- CE | cETLus



# CYBER PAK



3-in-1 Audio Management System

## ORDERING INFORMATION

SKU (US)	SKU (EU)	DESCRIPTION
CYBER PAK	N/A	Elation Cyber Pak



## UNIT DIMENSIONS

